

**SYSTEM AND METHOD FOR AUTOMATICALLY GENERATING
A HIERARCHICAL REGISTER CONSOLIDATION STRUCTURE**

Inventors: Michael A. Holmes
104 Johanson Avenue
Hillsborough, New Jersey 08844
County: Somerset
Citizenship: United Kingdom

Gerald S. Williams
2282 Woodbarn Road
Macungie, Pennsylvania 18062
County: Lehigh
Citizenship: U.S.A.

Assignee: Agere Systems Incorporated
1110 American Parkway NE
Allentown, Pennsylvania 18109

CERTIFICATE OF EXPRESS MAIL	
I hereby certify that this correspondence, including the attachments listed, is being deposited with the United States Postal Service, Express Mail - Post Office to Addressee, Receipt No. <u>EV316267353US</u> , in an envelope addressed to Commissioner for Patents, Alexandria, VA22313, on the date shown below.	
<u>03-16-2004</u> Date of Mailing	<u>Stephanie Pritt</u> Typed or printed name of person mailing
	<u>Stephanie Pritt</u> Signature of person mailing

Hitt Gaines, P.C.
P.O. Box 832570
Richardson, Texas 75083
(972) 480-8800

**SYSTEM AND METHOD FOR AUTOMATICALLY GENERATING
A HIERARCHICAL REGISTER CONSOLIDATION STRUCTURE**

CROSS-REFERENCE TO RELATED APPLICATIONS

[0001] This application is related to U.S. Patent Application Serial No. 10/612,097 entitled "A Condition Management System and Method of Operation Thereof" to Eckhart, et al., filed on July 2, 2003, and U.S. Patent Application Serial No. 10/782,080 entitled "A Condition Management Callback System and Method of Operation Thereof" to Hitchcock, et al., filed on February 19, 2004, both of which are commonly assigned with the present invention and incorporated herein by reference as if reproduced herein in their entirety.

TECHNICAL FIELD OF THE INVENTION

[0002] The present invention is directed, in general, to processors and, more specifically, to a system and method for automatically generating a hierarchical register consolidation structure.

LIMITED COPYRIGHT WAIVER

[0003] A portion of the disclosure of this patent document contains material to which the claim of copyright protection is made. The copyright owner has no objection to the facsimile reproduction by any person of the patent document or the patent disclosure, as it appears in the U.S. Patent and Trademark Office file or records, but reserves all other rights whatsoever.

BACKGROUND OF THE INVENTION

[0004] Computer systems perform wide-ranging tasks in today's world, to say the least. In performing many of these tasks, computers are called upon to determine the condition of and control external devices. These external devices may be of many different types, including sensors, clocks, actuators, disk drives and motors to name just a few.

[0005] A computer typically interacts with external devices by executing a software program that calls for the computer to generate signals that control certain of the devices based on the condition of other of the devices. For example, a computer may adjust the speed of a motor based on the temperature of a fluid that the motor is stirring and the length of time that the motor has been stirring the fluid.

[0006] When computers began to be called upon to sense and control external devices, a method called "polling" was developed. Polling calls for the computer actively to query the external devices to determine their condition, usually periodically. In the example above, the computer may poll a thermometer and a clock once a second to determine the fluid temperature and time. While effective for simple tasks involving a relatively small number of devices, polling came to consume ever-greater amounts of the computer's time as the tasks and the numbers of devices became more complex. Polling is inefficient, because the computer must poll even when no conditions requiring the computer's response have occurred. At its extreme, polling may even consume so much time that the computer is precluded from performing other tasks.

[0007] To overcome the disadvantages inherent in polling, "interrupts" were developed. With interrupts, the computer does not actively determine the condition of external devices. Instead, changes in device condition ("events") cause signals ("interrupts") to be delivered to the computer, often by way of an "interrupt register," or "alarm register," that contains status information regarding its corresponding external device. The computer is free to execute its software program until it receives an interrupt, at which time it usually departs from its program and responds to, or "handles," the interrupt, often based on the contents of one or more interrupt registers.

[0008] Interrupts are widely used today, but they are by no means a perfect solution by themselves. Interrupt handling becomes complex when a computer is called upon to sense and control a great number of external devices, such as may be encountered in a telecommunications or computer network. It becomes more complex when combinations of events trigger different responses by the computer. It becomes still more complex when the events and combinations change depending upon the software instructions that the computer is executing when the events or combinations occur. Combinations of interrupt conditions have become so complex that they are now often organized into a "hierarchical register consolidation structure" to ease their management. Management of the hierarchical register consolidation structure may be performed by a condition management system, or CMS.

[0009] Creating a suitable hierarchical register consolidation structure for a system of external devices, however, remains a time-consuming challenge. When a new system is designed, its microprocessor-accessible registers, node interrelationships and summary bits and masks associated with its alarm registers are currently carefully, manually organized into a register consolidation structure that is traversable as a mathematical tree. Systems having many thousands of such registers, interrelationships, summary bits and masks can render the process extremely tedious and exceedingly error-prone. Creating, testing

and correcting errors in manually produced hierarchical register consolidation structures takes significant development time and money and can significantly complicate and delay the introduction of new systems. What is needed in the art is a faster, more accurate way to create a hierarchical register consolidation structure.

SUMMARY OF THE INVENTION

[0010] To address the above-discussed deficiencies of the prior art, the present invention, in one aspect, provides a system for automatically generating a hierarchical register consolidation structure.

[0011] In one embodiment, the system includes: (1) a graph generator that parses a High-level Design Language (HDL) file to generate an intermediate graph containing definitions of microprocessor-accessible registers, node interrelationships and summary bits and masks associated with alarm registers, (2) a graph converter, associated with the graph generator, that selectively adds virtual elements and nodes to the intermediate graph to transform the intermediate graph into a mathematical tree and (3) a description generator, associated with the graph converter, that employs the mathematical tree to generate a static tree description in a programming language suitable for use by a device-independent condition management structure.

[0012] In another aspect, the present invention provides a method of automatically generating a hierarchical register consolidation structure. In one embodiment, the method includes: (1) parsing a High-level Design Language (HDL) file to generate an intermediate graph containing definitions of microprocessor-accessible registers, node interrelationships and summary bits and

masks associated with alarm registers, (2) selectively adding virtual elements and nodes to the intermediate graph to transform the intermediate graph into a mathematical tree and (3) employing the mathematical tree to generate a static tree description in a programming language suitable for use by a device-independent condition management structure.

[0013] In yet another aspect, the present invention provides a system for automatically generating a hierarchical register consolidation structure. In one embodiment, the system includes: (1) a graph generator that parses a High-level Design Language (HDL) file to generate an intermediate graph containing definitions of microprocessor-accessible registers, node interrelationships and summary bits, bit offsets and masks associated with alarm registers, (2) a graph converter, associated with the graph generator, that selectively adds virtual elements and nodes to the intermediate graph to transform the intermediate graph into a mathematical tree and (3) a description generator, associated with the graph converter, that employs the mathematical tree to generate a static tree description in a programming language suitable for use by a device-independent condition management structure and an HTML traversable tree representation based on the mathematical tree.

[0014] The foregoing has outlined, rather broadly, preferred and alternative features of the present invention so that those skilled

in the art may better understand the detailed description of the invention that follows. Additional features of the invention will be described hereinafter that form the subject of the claims of the invention. Those skilled in the art should appreciate that they can readily use the disclosed conception and specific embodiment as a basis for designing or modifying other structures for carrying out the same purposes of the present invention. Those skilled in the art should also realize that such equivalent constructions do not depart from the spirit and scope of the invention in its broadest form.

BRIEF DESCRIPTION OF THE DRAWINGS

[0015] For a more complete understanding of the present invention, reference is now made to the following descriptions taken in conjunction with the accompanying drawings, in which:

[0016] FIGURE 1 illustrates a block diagram of a system for automatically generating a hierarchical register consolidation structure constructed according to the principles of the present invention; and

[0017] FIGURE 2 illustrates a flow diagram of a method of automatically generating a hierarchical register consolidation structure carried out according to the principles of the present invention.

DETAILED DESCRIPTION

[0018] Referring initially to FIGURE 1, illustrated is a block diagram of a system, generally designated 100, for automatically generating a hierarchical register consolidation structure constructed according to the principles of the present invention.

[0019] The system 100 includes a graph generator 110. The graph generator 110 parses a High-level Design Language (HDL) file 105, which may be a Verilog HDL file. HDL tools and the files they produce are well known to those skilled in the pertinent art. In the illustrated embodiment, the HDL file 105 is produced by a particular hardware description tool called "OTUS." Of course, other HDL file generating tools fall within the broad scope of the present invention. Table 1, below, illustrates an exemplary OTUS microprocessor interface hardware description language file that can be the HDL file 105.

```
// VPP - width of internal data bus (per channel)
// VPP - number of physical channels terminated
// VPP - number of physical channels terminated on Primary Line interface
// VPP - number of data words per column

// VPP - width of data parity bus (design assumes 1 bit per 8 bits data)

// VPP - width of Rx & Tx Line Data Busses

// VPP - sts = 1 to max_num_sts

// VPP - col = 1 to max_num_col
//`let frame_col_size = CEIL(LOG2(`max_num_col+1))

// VPP - row = 1 to 9

// VPP - number of STS-12s per channel

// VPP - number of STS-12 drop links

// VPP - number of STS-12 add links

// VPP - width of address bus for external processor interface

// VPP - width of data bus for external processor interface

// VPP - width of parity bus for external processor interface
```

```

// VPP - width of address bus between MPIF and SPIFs

//*****
//*
//* Parameters
//*
//*****

`define single_ch 0
`define sonet_mode 0
`define sdh_mode 1

// standard/advanced framing constants
`define enh_frmg 1'b1
`define std_frmg 1'b0

address_bus_width 16;
data_bus_width 16;

//`let ms_addr_bit = `i_add_width - 1

spif align_spif spif_address_width = 8 [7:0];

output [10:0] ALIGN_ISR;

////////////////////////////////////
//
domain align_common
    clock = CLK,
    reset_signal = RST_N,
    selection = ALIGN_COM_SEL,
    transfer_type = fast;

addr = 8'h00;

//-----
// INTERRUPT STATUS REGISTER: STS-12 and STS-48 Port Channel Alarms
isreg [10:0] ALIGN_ISR, address = addr,,
ALIGN_ISR_MASK
{
    0 : ALIGN_CH_W_Q1 {
ALIGN_W_CH_ALARM_1[3:0],
ALIGN_W_CH_ALARM_2[7:4],
ALIGN_W_CH_ALARM_3[11:8],
ALIGN_W_CH_ALARM_4[15:12]},
    1 : ALIGN_CH_W_Q2 {
ALIGN_W_CH_ALARM_5[3:0],
ALIGN_W_CH_ALARM_6[7:4],
ALIGN_W_CH_ALARM_7[11:8],
ALIGN_W_CH_ALARM_8[15:12]},
    2 : ALIGN_CH_W_Q3 {
ALIGN_W_CH_ALARM_9[3:0],
ALIGN_W_CH_ALARM_10[7:4],
ALIGN_W_CH_ALARM_11[11:8],
ALIGN_W_CH_ALARM_12[15:12]},
    3 : ALIGN_CH_W_Q4 {
ALIGN_W_CH_ALARM_13[3:0],
ALIGN_W_CH_ALARM_14[7:4],
ALIGN_W_CH_ALARM_15[11:8],
ALIGN_W_CH_ALARM_16[15:12]},
    4 : ALIGN_CH_P_Q1 {
ALIGN_P_CH_ALARM_1[3:0],
ALIGN_P_CH_ALARM_2[7:4],
ALIGN_P_CH_ALARM_3[11:8],
ALIGN_P_CH_ALARM_4[15:12]},
    5 : ALIGN_CH_P_Q2 {
ALIGN_P_CH_ALARM_5[3:0],
ALIGN_P_CH_ALARM_6[7:4],
ALIGN_P_CH_ALARM_7[11:8],
ALIGN_P_CH_ALARM_8[15:12]},
    6 : ALIGN_CH_P_Q3 {
ALIGN_P_CH_ALARM_9[3:0],
ALIGN_P_CH_ALARM_10[7:4],
ALIGN_P_CH_ALARM_11[11:8],
ALIGN_P_CH_ALARM_12[15:12]},
    7 : ALIGN_CH_P_Q4 {
ALIGN_P_CH_ALARM_13[3:0],
ALIGN_P_CH_ALARM_14[7:4],
ALIGN_P_CH_ALARM_15[11:8],
ALIGN_P_CH_ALARM_16[15:12]},
    8 : ALIGN_CH48_W_1 {
ALIGN_W_CH48_ALARM_1[3:0],
ALIGN_W_CH48_ALARM_2[7:4],

```

```

ALIGN_W_CH48_ALARM_3[11:8],
ALIGN_W_CH48_ALARM_4[15:12]],
    9 : ALIGN_CH48_P_1 {
ALIGN_P_CH48_ALARM_1[3:0],
ALIGN_P_CH48_ALARM_2[7:4],
ALIGN_P_CH48_ALARM_3[11:8],
ALIGN_P_CH48_ALARM_4[15:12]],
10 : ALIGN_COMMON { ALIGN_COM_ALARM[1:0] }
};

bit_description ALIGN_ISR "Alignment Processor Interrupt Status Register"
    ALIGN_CH_W_1[0] "WORK: Alignment Processor STS-12 Quadrant 1 Alarms",
    ALIGN_CH_W_2[1] "WORK: Alignment Processor STS-12 Quadrant 2 Alarms",
    ALIGN_CH_W_3[2] "WORK: Alignment Processor STS-12 Quadrant 3 Alarms",
    ALIGN_CH_W_4[3] "WORK: Alignment Processor STS-12 Quadrant 4 Alarms",
    ALIGN_CH_P_1[4] "PROTECT: Alignment Processor STS-12 Quadrant 1 Alarms",
    ALIGN_CH_P_2[5] "PROTECT: Alignment Processor STS-12 Quadrant 2 Alarms",
    ALIGN_CH_P_3[6] "PROTECT: Alignment Processor STS-12 Quadrant 3 Alarms",
    ALIGN_CH_P_4[7] "PROTECT: Alignment Processor STS-12 Quadrant 4 Alarms",
    ALIGN_CH48_W_1[8] "WORK: Alignment Processor STS-48 Alarms",
    ALIGN_CH48_P_1[9] "PROTECT: Alignment Processor STS-48 Alarms",
    ALIGN_COMMON[10] "Alignment Processor Common Alarms";

//-----
// INTERRUPT ENABLE REGISTER: STS-12 and STS-48 Port Channel Alarms Interrupt Enable
iereg [10:0] ALIGN_ISR_MASK, address = addr,;;

bit_description ALIGN_ISR_MASK "Alignment Processor Interrupt Status Mask Register"
    ALIGN_CH_W_M1[0] "WORK: Alignment Processor STS-12 Quadrant 1 Alarms Mask",
    ALIGN_CH_W_M2[1] "WORK: Alignment Processor STS-12 Quadrant 2 Alarms Mask",
    ALIGN_CH_W_M3[2] "WORK: Alignment Processor STS-12 Quadrant 3 Alarms Mask",
    ALIGN_CH_W_M4[3] "WORK: Alignment Processor STS-12 Quadrant 4 Alarms Mask",
    ALIGN_CH_P_M1[4] "PROTECT: Alignment Processor STS-12 Quadrant 1 Alarms Mask",
    ALIGN_CH_P_M2[5] "PROTECT: Alignment Processor STS-12 Quadrant 2 Alarms Mask",
    ALIGN_CH_P_M3[6] "PROTECT: Alignment Processor STS-12 Quadrant 3 Alarms Mask",
    ALIGN_CH_P_M4[7] "PROTECT: Alignment Processor STS-12 Quadrant 4 Alarms Mask",
    ALIGN_CH48_W_M1[8] "WORK: Alignment Processor STS-48 Alarms Mask",
    ALIGN_CH48_P_M1[9] "PROTECT: Alignment Processor STS-48 Alarms Mask",
    ALIGN_COMMON_M[10] "Alignment Processor Common Alarms Mask";

//-----
// CONTROL REGISTER: Min Threshold for FIFO (Per Quadrant)
group FMIN creg [5:0] FIFO_MIN_1, address = addr, , ;

bit_def FIFO_MIN_1 "FIFO Minimum Threshold Control Register Quadrant %d"
THRESH_Q[5:0]
"THRESH_ERR is triggered if FIFO_DEPTH is less than this value";

clone_reg FIFO_MIN_1, add_to_the_group FMIN, number_of_clones=3, address_offset=8'h01,;

//-----
// CONTROL REGISTER: Max Threshold for FIFO (Per Quadrant)
group FMAX creg [5:0] FIFO_MAX_1, address = addr, reset_value=6'd63, ;

bit_def FIFO_MAX_1 "FIFO Maximum Threshold Control Register Quadrant %d"
THRESH_Q[5:0]
"THRESH_ERR is triggered if FIFO_DEPTH is greater than this value";

clone_reg FIFO_MAX_1, add_to_the_group FMAX, number_of_clones=3, address_offset=8'h01,;

//-----
// CONTROL REGISTER: Add Frame Offset
creg [14:0] ADD_FRM_CTRL, address = addr,;;

bit_def ADD_FRM_CTRL "AFRM Offset Control"
DEJ_DIS [14] "AFRM Dejitter Disable control",
OFFSET_COUNT [13:0]
"AFRM Frame Pulse Internal Offset Position
(Multiples of 78MHz clock cycles)";

//-----
// CONTROL REGISTER: Resynchronization control
creg [1:0] ALIGN_RESYNC_CTRL, address = addr,;;

bit_def ALIGN_RESYNC_CTRL "Aligner Resynchronization Control"
RESYNC[0]
"WORK/PROTECT: A 0->1 transition on this bit will force a resync.",
SEF_RESYNC_EN[1]
"WORK/PROTECT: When enabled a resync will be automatically issued if all
the enabled channels go into SEF and at least one recovers.";

//-----

```

```

// CONTROL REGISTER: Spare Register
creg [15:0] ALIGN_SPARE_REG, address = addr,;

bit_description ALIGN_SPARE_REG "Align Processor Spare Register"
ALIGN_SPARE_REG[15:0] "Reserved Use";

//-----
// ALARM REGISTER: Common Alarms
iareg [1:0] ALIGN_COM_ALARM, address = addr,;
ALIGN_COM_MASK;

bit_def ALIGN_COM_ALARM "Align Common Alarms"
AFRM_LOF [0] "AFRM Loss of Frame",
AFRM_RESYNC [1] "AFRM Re-synchronization Alarm";

iereg [1:0] ALIGN_COM_MASK, address = addr,;

bit_description ALIGN_COM_MASK "Align Common Interrupt Alarm Mask Register"
AFRM_LOF_M [0] "AFRM Loss of Frame Mask",
AFRM_RESYNC_M [1] "AFRM Re-synchronization Alarm Mask";

enddomain

////////////////////////////////////
// WORK: CHANNELS ALIGNER REGISTERS
domain align_w_ch
clock = W_CLK,
reset_signal = W_RST_N,
selection = ALIGN_W_CH_SEL,
transfer_type = fast;

addr = 8'h00;

//-----
// INTERRUPT ALARM REGISTER: Working Channel Alarms

iareg [3:0] ALIGN_W_CH_ALARM_1, address = addr,;ALIGN_W_CH_MASK_1;
bit_def ALIGN_W_CH_ALARM_1 "WORK: Alignment Processor STS-12 Channels 1 to 4 Interrupt Alarm Register"
SYNC_LIMIT_ERR[0] "WORK: The Channels to be Synced are too far apart",
ALIGN_ERR[1] "WORK: The Frame Pulses from Synced Channels don't match",
FIFO_WINDOW_ERR[2] "WORK: This Channel Cannot be Aligned using the Current FIFO Window",
THRESH_ERR[3] "WORK: The Depth of this Channel is >FIFO_MAX or <FIFO_MIN";

iereg [3:0] ALIGN_W_CH_MASK_1, address = addr,;
bit_description ALIGN_W_CH_MASK_1 "WORK: Alignment Processor STS-12 Channels 1 to 4 Interrupt Alarm Mask Register"
SYNC_LIMIT_ERR[0] "WORK: The Channels to be Synced are too far apart Mask",
ALIGN_ERR[1] "WORK: The Frame Pulses from Synced Channels don't match Mask",
FIFO_WINDOW_ERR[2] "WORK: This Channel Cannot be Aligned using the Current FIFO Window Mask",
THRESH_ERR[3] "WORK: The Depth of this Channel is >FIFO_MAX or <FIFO_MIN Mask";

addr = 2;

iareg [7:4] ALIGN_W_CH_ALARM_2, address = addr,;ALIGN_W_CH_MASK_2;
bit_def ALIGN_W_CH_ALARM_2 "WORK: Alignment Processor STS-12 Channels 2 to 5 Interrupt Alarm Register"
SYNC_LIMIT_ERR[4] "WORK: The Channels to be Synced are too far apart",
ALIGN_ERR[5] "WORK: The Frame Pulses from Synced Channels don't match",
FIFO_WINDOW_ERR[6] "WORK: This Channel Cannot be Aligned using the Current FIFO Window",
THRESH_ERR[7] "WORK: The Depth of this Channel is >FIFO_MAX or <FIFO_MIN";

iereg [7:4] ALIGN_W_CH_MASK_2, address = addr,;
bit_description ALIGN_W_CH_MASK_2 "WORK: Alignment Processor STS-12 Channels 2 to 5 Interrupt Alarm Mask Register"
SYNC_LIMIT_ERR[4] "WORK: The Channels to be Synced are too far apart Mask",
ALIGN_ERR[5] "WORK: The Frame Pulses from Synced Channels don't match Mask",
FIFO_WINDOW_ERR[6] "WORK: This Channel Cannot be Aligned using the Current FIFO Window Mask",
THRESH_ERR[7] "WORK: The Depth of this Channel is >FIFO_MAX or <FIFO_MIN Mask";

addr = 2;

iareg [11:8] ALIGN_W_CH_ALARM_3, address = addr,;ALIGN_W_CH_MASK_3;
bit_def ALIGN_W_CH_ALARM_3 "WORK: Alignment Processor STS-12 Channels 3 to 6 Interrupt Alarm Register"
SYNC_LIMIT_ERR[8] "WORK: The Channels to be Synced are too far apart",
ALIGN_ERR[9] "WORK: The Frame Pulses from Synced Channels don't match",
FIFO_WINDOW_ERR[10] "WORK: This Channel Cannot be Aligned using the Current FIFO Window",
THRESH_ERR[11] "WORK: The Depth of this Channel is >FIFO_MAX or <FIFO_MIN";

iereg [11:8] ALIGN_W_CH_MASK_3, address = addr,;
bit_description ALIGN_W_CH_MASK_3 "WORK: Alignment Processor STS-12 Channels 3 to 6 Interrupt Alarm Mask Register"
SYNC_LIMIT_ERR[8] "WORK: The Channels to be Synced are too far apart Mask",
ALIGN_ERR[9] "WORK: The Frame Pulses from Synced Channels don't match Mask",

```

```

FIFO_WINDOW_ERR[10] "WORK: This Channel Cannot be Aligned using the Current FIFO Window Mask",
THRESH_ERR[11]      "WORK: The Depth of this Channel is >FIFO_MAX or <FIFO_MIN Mask";

addr - = 2;

iareg [15:12] ALIGN_W_CH_ALARM_4, address = addr,,ALIGN_W_CH_MASK_4;
bit_def ALIGN_W_CH_ALARM_4 "WORK: Alignment Processor STS-12 Channels 4 to 7 Interrupt Alarm Register"
SYNC_LIMIT_ERR[12] "WORK: The Channels to be Synced are too far apart",
ALIGN_ERR[13]      "WORK: The Frame Pulses from Synced Channels don't match",
FIFO_WINDOW_ERR[14] "WORK: This Channel Cannot be Aligned using the Current FIFO Window",
THRESH_ERR[15]      "WORK: The Depth of this Channel is >FIFO_MAX or <FIFO_MIN";

iareg [15:12] ALIGN_W_CH_MASK_4, address = addr,,;
bit_description ALIGN_W_CH_MASK_4 "WORK: Alignment Processor STS-12 Channels 4 to 7 Interrupt Alarm Mask Register"
SYNC_LIMIT_ERR[12] "WORK: The Channels to be Synced are too far apart Mask",
ALIGN_ERR[13]      "WORK: The Frame Pulses from Synced Channels don't match Mask",
FIFO_WINDOW_ERR[14] "WORK: This Channel Cannot be Aligned using the Current FIFO Window Mask",
THRESH_ERR[15]      "WORK: The Depth of this Channel is >FIFO_MAX or <FIFO_MIN Mask";

//-----
// INTERRUPT ALARM REGISTER: Working Channel Alarms

iareg [3:0] ALIGN_W_CH_ALARM_5, address = addr,,ALIGN_W_CH_MASK_5;
bit_def ALIGN_W_CH_ALARM_5 "WORK: Alignment Processor STS-12 Channels 5 to 8 Interrupt Alarm Register"
SYNC_LIMIT_ERR[0] "WORK: The Channels to be Synced are too far apart",
ALIGN_ERR[1]      "WORK: The Frame Pulses from Synced Channels don't match",
FIFO_WINDOW_ERR[2] "WORK: This Channel Cannot be Aligned using the Current FIFO Window",
THRESH_ERR[3]      "WORK: The Depth of this Channel is >FIFO_MAX or <FIFO_MIN";

iareg [3:0] ALIGN_W_CH_MASK_5, address = addr,,;
bit_description ALIGN_W_CH_MASK_5 "WORK: Alignment Processor STS-12 Channels 5 to 8 Interrupt Alarm Mask Register"
SYNC_LIMIT_ERR[0] "WORK: The Channels to be Synced are too far apart Mask",
ALIGN_ERR[1]      "WORK: The Frame Pulses from Synced Channels don't match Mask",
FIFO_WINDOW_ERR[2] "WORK: This Channel Cannot be Aligned using the Current FIFO Window Mask",
THRESH_ERR[3]      "WORK: The Depth of this Channel is >FIFO_MAX or <FIFO_MIN Mask";

addr - = 2;

iareg [7:4] ALIGN_W_CH_ALARM_6, address = addr,,ALIGN_W_CH_MASK_6;
bit_def ALIGN_W_CH_ALARM_6 "WORK: Alignment Processor STS-12 Channels 6 to 9 Interrupt Alarm Register"
SYNC_LIMIT_ERR[4] "WORK: The Channels to be Synced are too far apart",
ALIGN_ERR[5]      "WORK: The Frame Pulses from Synced Channels don't match",
FIFO_WINDOW_ERR[6] "WORK: This Channel Cannot be Aligned using the Current FIFO Window",
THRESH_ERR[7]      "WORK: The Depth of this Channel is >FIFO_MAX or <FIFO_MIN";

iareg [7:4] ALIGN_W_CH_MASK_6, address = addr,,;
bit_description ALIGN_W_CH_MASK_6 "WORK: Alignment Processor STS-12 Channels 6 to 9 Interrupt Alarm Mask Register"
SYNC_LIMIT_ERR[4] "WORK: The Channels to be Synced are too far apart Mask",
ALIGN_ERR[5]      "WORK: The Frame Pulses from Synced Channels don't match Mask",
FIFO_WINDOW_ERR[6] "WORK: This Channel Cannot be Aligned using the Current FIFO Window Mask",
THRESH_ERR[7]      "WORK: The Depth of this Channel is >FIFO_MAX or <FIFO_MIN Mask";

addr - = 2;

iareg [11:8] ALIGN_W_CH_ALARM_7, address = addr,,ALIGN_W_CH_MASK_7;
bit_def ALIGN_W_CH_ALARM_7 "WORK: Alignment Processor STS-12 Channels 7 to 10 Interrupt Alarm Register"
SYNC_LIMIT_ERR[8] "WORK: The Channels to be Synced are too far apart",
ALIGN_ERR[9]      "WORK: The Frame Pulses from Synced Channels don't match",
FIFO_WINDOW_ERR[10] "WORK: This Channel Cannot be Aligned using the Current FIFO Window",
THRESH_ERR[11]      "WORK: The Depth of this Channel is >FIFO_MAX or <FIFO_MIN";

iareg [11:8] ALIGN_W_CH_MASK_7, address = addr,,;
bit_description ALIGN_W_CH_MASK_7 "WORK: Alignment Processor STS-12 Channels 7 to 10 Interrupt Alarm Mask Register"
SYNC_LIMIT_ERR[8] "WORK: The Channels to be Synced are too far apart Mask",
ALIGN_ERR[9]      "WORK: The Frame Pulses from Synced Channels don't match Mask",
FIFO_WINDOW_ERR[10] "WORK: This Channel Cannot be Aligned using the Current FIFO Window Mask",
THRESH_ERR[11]      "WORK: The Depth of this Channel is >FIFO_MAX or <FIFO_MIN Mask";

addr - = 2;

iareg [15:12] ALIGN_W_CH_ALARM_8, address = addr,,ALIGN_W_CH_MASK_8;
bit_def ALIGN_W_CH_ALARM_8 "WORK: Alignment Processor STS-12 Channels 8 to 11 Interrupt Alarm Register"
SYNC_LIMIT_ERR[12] "WORK: The Channels to be Synced are too far apart",
ALIGN_ERR[13]      "WORK: The Frame Pulses from Synced Channels don't match",
FIFO_WINDOW_ERR[14] "WORK: This Channel Cannot be Aligned using the Current FIFO Window",
THRESH_ERR[15]      "WORK: The Depth of this Channel is >FIFO_MAX or <FIFO_MIN";

iareg [15:12] ALIGN_W_CH_MASK_8, address = addr,,;
bit_description ALIGN_W_CH_MASK_8 "WORK: Alignment Processor STS-12 Channels 8 to 11 Interrupt Alarm Mask Register"
SYNC_LIMIT_ERR[12] "WORK: The Channels to be Synced are too far apart Mask",
ALIGN_ERR[13]      "WORK: The Frame Pulses from Synced Channels don't match Mask",

```

```

FIFO_WINDOW_ERR[14] "WORK: This Channel Cannot be Aligned using the Current FIFO Window Mask",
THRESH_ERR[15]      "WORK: The Depth of this Channel is >FIFO_MAX or <FIFO_MIN Mask";

//-----
// INTERRUPT ALARM REGISTER: Working Channel Alarms

iareg [3:0] ALIGN_W_CH_ALARM_9, address = addr,,ALIGN_W_CH_MASK_9;
bit_def ALIGN_W_CH_ALARM_9 "WORK: Alignment Processor STS-12 Channels 9 to 12 Interrupt Alarm Register"
  SYNC_LIMIT_ERR[0] "WORK: The Channels to be Synced are too far apart",
  ALIGN_ERR[1]      "WORK: The Frame Pulses from Synced Channels don't match",
  FIFO_WINDOW_ERR[2] "WORK: This Channel Cannot be Aligned using the Current FIFO Window",
  THRESH_ERR[3]      "WORK: The Depth of this Channel is >FIFO_MAX or <FIFO_MIN";

iareg [3:0] ALIGN_W_CH_MASK_9, address = addr,,;
bit_description ALIGN_W_CH_MASK_9 "WORK: Alignment Processor STS-12 Channels 9 to 12 Interrupt Alarm Mask Register"
  SYNC_LIMIT_ERR[0] "WORK: The Channels to be Synced are too far apart Mask",
  ALIGN_ERR[1]      "WORK: The Frame Pulses from Synced Channels don't match Mask",
  FIFO_WINDOW_ERR[2] "WORK: This Channel Cannot be Aligned using the Current FIFO Window Mask",
  THRESH_ERR[3]      "WORK: The Depth of this Channel is >FIFO_MAX or <FIFO_MIN Mask";

addr - = 2;

iareg [7:4] ALIGN_W_CH_ALARM_10, address = addr,,ALIGN_W_CH_MASK_10;
bit_def ALIGN_W_CH_ALARM_10 "WORK: Alignment Processor STS-12 Channels 10 to 13 Interrupt Alarm Register"
  SYNC_LIMIT_ERR[4] "WORK: The Channels to be Synced are too far apart",
  ALIGN_ERR[5]      "WORK: The Frame Pulses from Synced Channels don't match",
  FIFO_WINDOW_ERR[6] "WORK: This Channel Cannot be Aligned using the Current FIFO Window",
  THRESH_ERR[7]      "WORK: The Depth of this Channel is >FIFO_MAX or <FIFO_MIN";

```

Table 1: Exemplary OTUS Microprocessor Interface
Hardware Description Language File

[0020] The graph generator 110 generates an intermediate graph 115 from the HDL file 105. In the illustrated embodiment, the graph generator 110 generates the intermediate graph 115 by making three passes through the HDL file 105. In a first pass, the graph generator 110 extracts the definitions of all the microprocessor-accessible registers, register names, addresses, bit positions used and their names. In a second pass, the graph generator 110 identifies node interrelationships and associates alarm registers with their mask register and persistency and delta information. In a third and final pass, the graph generator 110 associates summary bits in an alarm register with the alarm register that is summarized and generates bit offsets and masks are generated. The intermediate graph 115 that results after these three passes

therefore contains definitions of microprocessor-accessible registers, node interrelationships and summary bits and masks associated with alarm registers of the system of external devices to which the HDL file pertains. In the illustrated embodiment, the intermediate graph 115 further contains bit offsets associated with the alarm registers.

[0021] The system 100 further includes a graph converter 120. The graph converter 120 is associated with the graph generator 110 and receives the intermediate graph 115 therefrom. The graph converter 120 removes elements of the hardware interrupt tree that cause it to be a graph rather than a true mathematical tree. To do so, the graph converter 120 iterates over the intermediate graph identifying and creating virtual elements and virtual nodes that map to the same physical address. The graph converter 120 removes multiple parent situations and optionally modifies or prunes the intermediate graph 115 if sections of the system are not being used in a particular application. Pruning reduces the size of the resulting mathematical tree 125 and makes it faster to traverse. The resulting tree 125 is a true mathematical tree and can be used with a condition management system, or CMS, tool.

[0022] The system 100 further includes a description generator 130. The description generator 130 is associated with the graph converter 120. The description generator 130 employs the mathematical tree 125 to generate a static tree description 135 in

a programming language suitable for use by a device-independent CMS. In the illustrated embodiment, that programming language is C, though other programming languages fall within the broad scope of the present invention. Tables 2 and 3, below, illustrate exemplary static tree descriptions in C for both output nodes (Table 2) and output elements (Table 3).

```
static Node defaultTreeNode[] = {
{CHIP_SPIF_SEL_CHIP_STATUS_BIT_0,
  CHIP_SPIF_SEL_CHIP_ISR_1_BIT_0, 16, 0x0000, 0x0001,
  NON_EXISTENT, NON_EXISTENT, INT_CHIP_SPIF_SEL_CHIP_ISR_1},
{CHIP_SPIF_SEL_CHIP_STATUS_BIT_0_V0,
  CHIP_SPIF_SEL_CHIP_ISR_2_BIT_0, 25, 0x0002, 0x0003,
  NON_EXISTENT, NON_EXISTENT, INT_CHIP_SPIF_SEL_CHIP_ISR_2},
{invalidElem, CHIP_SPIF_SEL_CHIP_STATUS_BIT_0, 2, 0x0014,
  NON_EXISTENT, NON_EXISTENT, NON_EXISTENT,
  INT_CHIP_SPIF_SEL_CHIP_STATUS},
{CHIP_SPIF_SEL_CHIP_ISR_2_BIT_3,
  CHIP_SPIF_SEL_OH_CLK_LOSS_ALARM_ERTO_H_CLK_FAIL, 8,
  NON_EXISTENT, 0x001E, NON_EXISTENT, 0x001D,
  INT_CHIP_SPIF_SEL_OH_CLK_LOSS_ALARM},
{CHIP_SPIF_SEL_CHIP_ISR_2_BIT_13_V4,
  CHIP_SPIF_SEL_RDMX_RESYNC_BIT_0, 16, NON_EXISTENT, 0x0021,
  NON_EXISTENT, 0x0020, INT_CHIP_SPIF_SEL_RDMX_RESYNC},
{CHIP_SPIF_SEL_CHIP_ISR_2_BIT_13_V3,
  CHIP_SPIF_SEL_RMUX_TDMX_RESYNC_BIT_0, 8, NON_EXISTENT,
  0x0025, NON_EXISTENT, 0x0024,
  INT_CHIP_SPIF_SEL_RMUX_TDMX_RESYNC},
{CHIP_SPIF_SEL_CHIP_ISR_2_BIT_0,
  CHIP_SPIF_SEL_R_CLK_LOSS_ALARM_R_CLK_1_FAIL, 16,
  NON_EXISTENT, 0x0018, NON_EXISTENT, 0x0017,
  INT_CHIP_SPIF_SEL_R_CLK_LOSS_ALARM},
{CHIP_SPIF_SEL_CHIP_ISR_2_BIT_2,
  CHIP_SPIF_SEL_S_CLK_LOSS_ALARM_D_CLK_1_FAIL, 10,
  NON_EXISTENT, 0x001C, NON_EXISTENT, 0x001B,
  INT_CHIP_SPIF_SEL_S_CLK_LOSS_ALARM},
{CHIP_SPIF_SEL_CHIP_ISR_2_BIT_4,
  CHIP_SPIF_SEL_S_CLK_LOSS_ALARM_PM_CLK, 1, NON_EXISTENT,
  0x001C, NON_EXISTENT, 0x001B,
  INT_CHIP_SPIF_SEL_S_CLK_LOSS_ALARM_V0},
{CHIP_SPIF_SEL_CHIP_ISR_2_BIT_14_V6,
  CHIP_SPIF_SEL_S_RDMX_RESYNC_BIT_0, 16, NON_EXISTENT,
```

```

0x0027, NON_EXISTENT, 0x0026,
INT_CHIP_SPIF_SEL_S_RDMX_RESYNC},
{CHIP_SPIF_SEL_CHIP_ISR_2_BIT_14_V5,
CHIP_SPIF_SEL_S_RMUX_TDMX_RESYNC_BIT_0, 8, NON_EXISTENT,
0x002B, NON_EXISTENT, 0x002A,
INT_CHIP_SPIF_SEL_S_RMUX_TDMX_RESYNC},
{CHIP_SPIF_SEL_CHIP_ISR_2_BIT_14,
CHIP_SPIF_SEL_S_TMUX_RESYNC_BIT_0, 16, NON_EXISTENT,
0x0029, NON_EXISTENT, 0x0028,
INT_CHIP_SPIF_SEL_S_TMUX_RESYNC},
{CHIP_SPIF_SEL_CHIP_ISR_2_BIT_8, CHIP_SPIF_SEL_TIMED_INT_BIT_0,
1, NON_EXISTENT, 0x0016, NON_EXISTENT, 0x0015,
INT_CHIP_SPIF_SEL_TIMED_INT},
{CHIP_SPIF_SEL_CHIP_ISR_2_BIT_13,
CHIP_SPIF_SEL_TMUX_RESYNC_BIT_0, 16, NON_EXISTENT, 0x0023,
NON_EXISTENT, 0x0022, INT_CHIP_SPIF_SEL_TMUX_RESYNC},
{CHIP_SPIF_SEL_CHIP_ISR_2_BIT_1,
CHIP_SPIF_SEL_T_CLK_LOSS_ALARM_T_CLK_1_FAIL, 16,
NON_EXISTENT, 0x001A, NON_EXISTENT, 0x0019,
INT_CHIP_SPIF_SEL_T_CLK_LOSS_ALARM},
{EQPT_COMMON_SEL_EQPT_ISR_BIT_0,
EQPT_ADD_SEL_1_EQPT_TX_CH_ISR_BIT_0, 2, 0x7701, 0x7702,
NON_EXISTENT, NON_EXISTENT,
INT_EQPT_ADD_SEL_1_EQPT_TX_CH_ISR},
{EQPT_COMMON_SEL_EQPT_ISR_V0_BIT_0,
EQPT_ADD_SEL_1_EQPT_TX_CH_ISR_V0_BIT_0, 14, 0x7701,
0x7702, NON_EXISTENT, NON_EXISTENT}
}

```

Table 2: Static Tree Description in C:
Output Node Descriptions

```

static Elem defaultTreeElement[] = {
{INT_RX_LTE_SPIF_COMMON_SEL_LTE_ISR_1,
INT_CHIP_SPIF_SEL_CHIP_ISR_1, 0,
CHIP_SPIF_SEL_CHIP_ISR_1_BIT_0},
{INT_RX_LTE_SPIF_COMMON_SEL_LTE_ISR_1_V0,
INT_CHIP_SPIF_SEL_CHIP_ISR_1, 1,
CHIP_SPIF_SEL_CHIP_ISR_1_BIT_1},
{INT_RX_LTE_SPIF_COMMON_SEL_LTE_ISR_2,
INT_CHIP_SPIF_SEL_CHIP_ISR_1, 2,
CHIP_SPIF_SEL_CHIP_ISR_1_BIT_2},
{INT_RX_LTE_SPIF_COMMON_SEL_LTE_ISR_2_V0,
INT_CHIP_SPIF_SEL_CHIP_ISR_1, 3,
CHIP_SPIF_SEL_CHIP_ISR_1_BIT_3},
{INT_RX_LTE_SPIF_COMMON_SEL_LTE_ISR_3,

```

```

        INT_CHIP_SPIF_SEL_CHIP_ISR_1, 4,
        CHIP_SPIF_SEL_CHIP_ISR_1_BIT_4},
{INT_RX_LTE_SPIF_COMMON_SEL_LTE_ISR_3_V0,
        INT_CHIP_SPIF_SEL_CHIP_ISR_1, 5,
        CHIP_SPIF_SEL_CHIP_ISR_1_BIT_5},
{INT_RX_LTE_SPIF_COMMON_SEL_LTE_ISR_4,
        INT_CHIP_SPIF_SEL_CHIP_ISR_1, 6,
        CHIP_SPIF_SEL_CHIP_ISR_1_BIT_6},
{INT_RX_LTE_SPIF_COMMON_SEL_LTE_ISR_4_V0,
        INT_CHIP_SPIF_SEL_CHIP_ISR_1, 7,
        CHIP_SPIF_SEL_CHIP_ISR_1_BIT_7},
{INT_TX_LTE_SPIF_COMMON_SEL_LTE_ISR_1,
        INT_CHIP_SPIF_SEL_CHIP_ISR_1, 8,
        CHIP_SPIF_SEL_CHIP_ISR_1_BIT_8},
{INT_TX_LTE_SPIF_COMMON_SEL_LTE_ISR_1_V0,
        INT_CHIP_SPIF_SEL_CHIP_ISR_1, 9,
        CHIP_SPIF_SEL_CHIP_ISR_1_BIT_9},
{INT_RX_MEGA_POH_SEL_STS192_CH_ISR,
        INT_CHIP_SPIF_SEL_CHIP_ISR_1, 10,
        CHIP_SPIF_SEL_CHIP_ISR_1_BIT_10},
{INT_RX_MEGA_POH_SEL_STS192_CH_ISR_V0,
        INT_CHIP_SPIF_SEL_CHIP_ISR_1, 11,
        CHIP_SPIF_SEL_CHIP_ISR_1_BIT_11},
{INT_TX_MEGA_POH_SEL_STS192_CH_ISR,
        INT_CHIP_SPIF_SEL_CHIP_ISR_1, 12,
        CHIP_SPIF_SEL_CHIP_ISR_1_BIT_12},
{INT_TX_MEGA_POH_SEL_STS192_CH_ISR_V0,
        INT_CHIP_SPIF_SEL_CHIP_ISR_1, 13,
        CHIP_SPIF_SEL_CHIP_ISR_1_BIT_13},
{INT_EQPT_COMMON_SEL_EQPT_ISR,
        INT_CHIP_SPIF_SEL_CHIP_ISR_1, 14,
        CHIP_SPIF_SEL_CHIP_ISR_1_BIT_14},
{INT_EQPT_COMMON_SEL_EQPT_ISR_V1,
        INT_CHIP_SPIF_SEL_CHIP_ISR_1, 15,
        CHIP_SPIF_SEL_CHIP_ISR_1_BIT_15},
{INT_CHIP_SPIF_SEL_R_CLK_LOSS_ALARM,
        INT_CHIP_SPIF_SEL_CHIP_ISR_2, 0,
        CHIP_SPIF_SEL_CHIP_ISR_2_BIT_0},
{INT_CHIP_SPIF_SEL_T_CLK_LOSS_ALARM,
        INT_CHIP_SPIF_SEL_CHIP_ISR_2, 1,
        CHIP_SPIF_SEL_CHIP_ISR_2_BIT_1},
{INT_CHIP_SPIF_SEL_S_CLK_LOSS_ALARM,
        INT_CHIP_SPIF_SEL_CHIP_ISR_2, 2,
        CHIP_SPIF_SEL_CHIP_ISR_2_BIT_2},
{INT_CHIP_SPIF_SEL_OH_CLK_LOSS_ALARM,
        INT_CHIP_SPIF_SEL_CHIP_ISR_2, 3,
        CHIP_SPIF_SEL_CHIP_ISR_2_BIT_3},

```

```

{INT_CHIP_SPIF_SEL_S_CLK_LOSS_ALARM_V0,
  INT_CHIP_SPIF_SEL_CHIP_ISR_2, 4,
  CHIP_SPIF_SEL_CHIP_ISR_2_BIT_4},
{INT_RX_MEGA_SWITCH_SEL_MEGA_SWITCH_INT,
  INT_CHIP_SPIF_SEL_CHIP_ISR_2, 5,
  CHIP_SPIF_SEL_CHIP_ISR_2_BIT_5},
{INT_TX_MEGA_SWITCH_SEL_MEGA_SWITCH_INT,
  INT_CHIP_SPIF_SEL_CHIP_ISR_2, 6,
  CHIP_SPIF_SEL_CHIP_ISR_2_BIT_6},
{INT_EQPT_COMMON_SEL_EQPT_ISR_V0,
  INT_CHIP_SPIF_SEL_CHIP_ISR_2, 7,
  CHIP_SPIF_SEL_CHIP_ISR_2_BIT_7},
{INT_CHIP_SPIF_SEL_TIMED_INT,
  INT_CHIP_SPIF_SEL_CHIP_ISR_2, 8,
  CHIP_SPIF_SEL_CHIP_ISR_2_BIT_8},
{INT_LTE_RX_TRANS_SEL_1_TRANS_MEM_ISR,
  INT_CHIP_SPIF_SEL_CHIP_ISR_2, 9,
  CHIP_SPIF_SEL_CHIP_ISR_2_BIT_9},
{INT_LTE_TX_TRANS_SEL_1_TRANS_MEM_ISR,
  INT_CHIP_SPIF_SEL_CHIP_ISR_2, 10,
  CHIP_SPIF_SEL_CHIP_ISR_2_BIT_10},
{INT_RX_SERDES_SPIF_SEL_HCCR_X_ISR,
  INT_CHIP_SPIF_SEL_CHIP_ISR_2, 11,
  CHIP_SPIF_SEL_CHIP_ISR_2_BIT_11},
{INT_TX_SERDES_SPIF_SEL_HCCTX_ISR,
  INT_CHIP_SPIF_SEL_CHIP_ISR_2, 12,
  CHIP_SPIF_SEL_CHIP_ISR_2_BIT_12},
{INT_CHIP_SPIF_SEL_TMUX_RESYNC,
  INT_CHIP_SPIF_SEL_CHIP_ISR_2, 13,
  CHIP_SPIF_SEL_CHIP_ISR_2_BIT_13},
{INT_CHIP_SPIF_SEL_S_TMUX_RESYNC,
  INT_CHIP_SPIF_SEL_CHIP_ISR_2, 14,
  CHIP_SPIF_SEL_CHIP_ISR_2_BIT_14},
{INT_LTE_TX_TRANS_SEL_2_TRANS_MEM_ISR,
  INT_CHIP_SPIF_SEL_CHIP_ISR_2, 10,
  CHIP_SPIF_SEL_CHIP_ISR_2_BIT_10_V0}
}

```

Table 3: Static Tree Description in C:
Output Element Descriptions

[0023] In the illustrated embodiment, the description generator
130 further generates a HyperText Markup Language (HTML)
traversable tree representation 145 based on the mathematical tree

125. The static tree description 135 and/or the HTML traversable tree representation 145 form a hierarchical register consolidation structure. Tables 4, 5 and 6, below, illustrate exemplary HTML traversable tree representations for address 0x0, mask=0xffff (Table 4); address=0x2, mask=0x7fff (Table 5); and address=0x14, mask=0x7fff (Table 6). In Tables 4, 5 and 6, underlined numerals represent HTML hyperlinks.

Bit position Bit name	Direction Register name: contributing bit 1 , contributing bit N
Consolidation 0 CHIP_SPIF_SEL_CHIP_ISR_1_BIT_0 REAL bit 0	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>0</u> DOWN LINKS RX_LTE_SPIF_COMMON_SEL_LTE_ISR _1: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>8</u>
Consolidation 1 CHIP_SPIF_SEL_CHIP_ISR_1_BIT_1 REAL bit 1	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>0</u> DOWN LINKS RX_LTE_SPIF_COMMON_SEL_LTE_ISR _1_V0: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>4</u> , <u>5</u> , <u>6</u> , <u>7</u> , <u>8</u>
Consolidation 2 CHIP_SPIF_SEL_CHIP_ISR_1_BIT_2 REAL bit 2	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>0</u> DOWN LINKS RX_LTE_SPIF_COMMON_SEL_LTE_ISR _2: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>8</u>
Consolidation 3 CHIP_SPIF_SEL_CHIP_ISR_1_BIT_3 REAL bit 3	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>0</u> DOWN LINKS RX_LTE_SPIF_COMMON_SEL_LTE_ISR _2_V0: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>4</u> , <u>5</u> , <u>6</u> , <u>7</u> , <u>8</u>
Consolidation 4 CHIP_SPIF_SEL_CHIP_ISR_1_BIT_4 REAL bit 4	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>0</u> DOWN LINKS RX_LTE_SPIF_COMMON_SEL_LTE_ISR _3: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>8</u>
Consolidation 5 CHIP_SPIF_SEL_CHIP_ISR_1_BIT_5 REAL bit 5	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>0</u> DOWN LINKS RX_LTE_SPIF_COMMON_SEL_LTE_ISR

	<u>3_V0: 0 , 1 , 2 , 3 , 4 , 5 , 6 , 7 , 8</u>
Consolidation 6 CHIP_SPIF_SEL_CHIP_ISR_1_BIT_6 REAL bit 6	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>0</u> DOWN LINKS RX_LTE_SPIF_COMMON_SEL_LTE_ISR _4: <u>0 , 1 , 2 , 3 , 8</u>
Consolidation 7 CHIP_SPIF_SEL_CHIP_ISR_1_BIT_7 REAL bit 7	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>0</u> DOWN LINKS RX_LTE_SPIF_COMMON_SEL_LTE_ISR _4_V0: <u>0 , 1 , 2 , 3 , 4 , 5 , 6 , 7 , 8</u>
Consolidation 8 CHIP_SPIF_SEL_CHIP_ISR_1_BIT_8 REAL bit 8	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>0</u> DOWN LINKS TX_LTE_SPIF_COMMON_SEL_LTE_ISR _1: <u>0 , 1 , 2 , 3 , 8 , 14 , 15 , 16</u>
Consolidation 9 CHIP_SPIF_SEL_CHIP_ISR_1_BIT_9 REAL bit 9	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>0</u> DOWN LINKS TX_LTE_SPIF_COMMON_SEL_LTE_ISR _1_V0: <u>0 , 1 , 2 , 3 , 4 , 5 , 6 , 7 , 8 , 9 , 10 , 11</u>
Consolidation 10 CHIP_SPIF_SEL_CHIP_ISR_1_BIT_1 0 REAL bit 10	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>0</u> DOWN LINKS RX_MEGA_POH_SEL_STS192_CH_ISR: <u>0 , 1 , 2 , 3 , 4 , 5 , 6 , 7 , 8 , 9 , 10 , 11</u>
Consolidation 11 CHIP_SPIF_SEL_CHIP_ISR_1_BIT_1 1 REAL bit 11	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>0</u> DOWN LINKS RX_MEGA_POH_SEL_STS192_CH_ISR_ V0: <u>0 , 1 , 2 , 3</u>
Consolidation 12 CHIP_SPIF_SEL_CHIP_ISR_1_BIT_1 2 REAL bit 12	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>0</u> DOWN LINKS TX_MEGA_POH_SEL_STS192_CH_ISR: <u>0 , 1 , 2 , 3 , 4 , 5 , 6 , 7 , 8 , 9 , 10 , 11</u>
Consolidation 13 CHIP_SPIF_SEL_CHIP_ISR_1_BIT_1 3 REAL bit 13	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>0</u> DOWN LINKS TX_MEGA_POH_SEL_STS192_CH_ISR_ V0: <u>0 , 1 , 2 , 3</u>
Consolidation 14	UP LINKS

CHIP_SPIF_SEL_CHIP_ISR_1_BIT_1 4 REAL bit 14	CHIP_SPIF_SEL_CHIP_STATUS: <u>0</u> DOWN LINKS EQPT_COMMON_SEL_EQPT_ISR: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>4</u>
Consolidation 15 CHIP_SPIF_SEL_CHIP_ISR_1_BIT_1 5 REAL bit 15	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>0</u> DOWN LINKS EQPT_COMMON_SEL_EQPT_ISR_V1: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u>

Table 4: HTML Traversable Tree Representation:
CHIP_SPIF_SEL_CHIP_ISR_1, Address=0x0, Mask=0xffff

Bit position Bit name	Direction Register name: contributing bit 1 ,contributing bit N
Consolidation 0 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_0 REAL bit 0	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS CHIP_SPIF_SEL_R_CLK_LOSS_ALARM: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>4</u> , <u>5</u> , <u>6</u> , <u>7</u> , <u>8</u> , <u>9</u> , <u>10</u> , <u>11</u> , <u>12</u> , <u>13</u> , <u>14</u> , <u>15</u>
Consolidation 1 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_1 REAL bit 1	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS CHIP_SPIF_SEL_T_CLK_LOSS_ALARM: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>4</u> , <u>5</u> , <u>6</u> , <u>7</u> , <u>8</u> , <u>9</u> , <u>10</u> , <u>11</u> , <u>12</u> , <u>13</u> , <u>14</u> , <u>15</u>
Consolidation 2 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_2 REAL bit 2	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS CHIP_SPIF_SEL_S_CLK_LOSS_ALARM: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>4</u> , <u>5</u> , <u>6</u> , <u>7</u> , <u>8</u> , <u>9</u>
Consolidation 3 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_3 REAL bit 3	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS CHIP_SPIF_SEL_OH_CLK_LOSS_ALARM: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>4</u> , <u>5</u> , <u>6</u> , <u>7</u>
Consolidation 4 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_4 REAL bit 4	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS CHIP_SPIF_SEL_S_CLK_LOSS_ALARM _V0: <u>0</u>
Consolidation 5 CHIP SPIF SEL CHIP ISR 2 BIT 5	UP LINKS CHIP SPIF SEL CHIP STATUS: <u>1</u>

REAL bit 5	DOWN LINKS RX_MEGA_SWITCH_SEL_TSI_SLICE12 SUMRY_INT: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>4</u> , <u>5</u> , <u>6</u> , <u>7</u> , <u>8</u> , <u>9</u> , <u>10</u> , <u>11</u> , <u>12</u> , <u>13</u> , <u>14</u> , <u>15</u>
Consolidation 6 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_6 REAL bit 6	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS TX_MEGA_SWITCH_SEL_TSI_SLICE12 SUMRY_INT: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>4</u> , <u>5</u> , <u>6</u> , <u>7</u> , <u>8</u> , <u>9</u> , <u>10</u> , <u>11</u> , <u>12</u> , <u>13</u> , <u>14</u> , <u>15</u>
Consolidation 7 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_7 REAL bit 7	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS EQPT_COMMON_SEL_EQPT_ISR_V0: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>4</u> , <u>5</u> , <u>6</u> , <u>7</u>
Consolidation 8 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_8 REAL bit 8	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS CHIP_SPIF_SEL_TIMED_INT: <u>0</u>
Consolidation 9 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_9 REAL bit 9	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS LTE_RX_TRANS_SEL_4_TRANS_MEM_I SR: <u>0</u>
Consolidation 10 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_1 0 REAL bit 10	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS LTE_TX_TRANS_SEL_4_TRANS_MEM_I SR: <u>0</u>
Consolidation 11 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_1 1 REAL bit 11	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS RX_SERDES_SPIF_SEL_HCCR_X_ISR: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>4</u> , <u>5</u> , <u>6</u> , <u>7</u> , <u>8</u> , <u>9</u> , <u>10</u> , <u>11</u> , <u>12</u> , <u>13</u> , <u>14</u> , <u>15</u> , <u>16</u> , <u>17</u>
Consolidation 12 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_1 2 REAL bit 12	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS TX_SERDES_SPIF_SEL_HCCTX_ISR: <u>0</u> , <u>1</u> , <u>2</u>
Consolidation 13 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_1 3 REAL bit 13	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS CHIP_SPIF_SEL_TMUX_RESYNC: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>4</u> , <u>5</u> , <u>6</u> , <u>7</u> , <u>8</u> ,

	<u>9</u> , <u>10</u> , <u>11</u> , <u>12</u> , <u>13</u> , <u>14</u> , <u>15</u>
Consolidation 14 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_1 4 REAL bit 14	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS CHIP_SPIF_SEL_S_TMUX_RESYNC: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>4</u> , <u>5</u> , <u>6</u> , <u>7</u> , <u>8</u> , <u>9</u> , <u>10</u> , <u>11</u> , <u>12</u> , <u>13</u> , <u>14</u> , <u>15</u>
Consolidation 15 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_1 0_V0 REAL bit 10	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS LTE_TX_TRANS_SEL_3_TRANS_MEM_ISR: <u>0</u>
Consolidation 16 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_1 0_V1 REAL bit 10	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS LTE_TX_TRANS_SEL_2_TRANS_MEM_ISR: <u>0</u>
Consolidation 17 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_1 0_V2 REAL bit 10	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS LTE_TX_TRANS_SEL_1_TRANS_MEM_ISR: <u>0</u>
Consolidation 18 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_1 3_V3 REAL bit 13	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS CHIP_SPIF_SEL_RDMX_RESYNC: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>4</u> , <u>5</u> , <u>6</u> , <u>7</u> , <u>8</u> , <u>9</u> , <u>10</u> , <u>11</u> , <u>12</u> , <u>13</u> , <u>14</u> , <u>15</u>
Consolidation 19 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_1 3_V4 REAL bit 13	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS CHIP_SPIF_SEL_RMUX_TDMX_RESYNC: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>4</u> , <u>5</u> , <u>6</u> , <u>7</u>
Consolidation 20 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_1 4_V5 REAL bit 14	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS CHIP_SPIF_SEL_S_RMUX_TDMX_RESY NC: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>4</u> , <u>5</u> , <u>6</u> , <u>7</u>
Consolidation 21 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_1 4_V6 REAL bit 14	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS CHIP_SPIF_SEL_S_RDMX_RESYNC: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>4</u> , <u>5</u> , <u>6</u> , <u>7</u> , <u>8</u> , <u>9</u> , <u>10</u> , <u>11</u> , <u>12</u> , <u>13</u> , <u>14</u> , <u>15</u>
Consolidation 22	UP LINKS

CHIP_SPIF_SEL_CHIP_ISR_2_BIT_9_V7 REAL bit 9	CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS LTE_RX_TRANS_SEL_3_TRANS_MEM_ISR: <u>0</u>
Consolidation 23 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_9_V8 REAL bit 9	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS LTE_RX_TRANS_SEL_2_TRANS_MEM_ISR: <u>0</u>
Consolidation 24 CHIP_SPIF_SEL_CHIP_ISR_2_BIT_9_V9 REAL bit 9	UP LINKS CHIP_SPIF_SEL_CHIP_STATUS: <u>1</u> DOWN LINKS LTE_RX_TRANS_SEL_1_TRANS_MEM_ISR: <u>0</u>

Table 5: HTML Traversable Tree Representation:
CHIP_SPIF_SEL_CHIP_ISR_2, Address=0x2, Mask=0x7fff

Bit position Bit name	Direction Register name: contributing bit 1, contributing bit N
Consolidation 0 CHIP_SPIF_SEL_CHIP_STATUS_BIT_0 REAL bit 0	DOWN LINKS CHIP_SPIF_SEL_CHIP_ISR_1: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>4</u> , <u>5</u> , <u>6</u> , <u>7</u> , <u>8</u> , <u>9</u> , <u>10</u> , <u>11</u> , <u>12</u> , <u>13</u> , <u>14</u> , <u>15</u>
Consolidation 1 CHIP_SPIF_SEL_CHIP_STATUS_BIT_0_V0 REAL bit 0	DOWN LINKS CHIP_SPIF_SEL_CHIP_ISR_2: <u>0</u> , <u>1</u> , <u>2</u> , <u>3</u> , <u>4</u> , <u>5</u> , <u>6</u> , <u>7</u> , <u>8</u> , <u>9</u> , <u>10</u> , <u>11</u> , <u>12</u> , <u>13</u> , <u>14</u> , <u>15</u> , <u>16</u> , <u>17</u> , <u>18</u> , <u>19</u> , <u>20</u> , <u>21</u> , <u>22</u> , <u>23</u> , <u>24</u>

Table 6: HTML Traversable Tree Representation:
CHIP_SPIF_SEL_CHIP_STATUS, Address=0x14, Mask=0x7fff

[0024] FIGURE 1 illustrates a CMS tool 150. The CMS tool 150 employs the static tree description 135 and/or the HTML traversable tree representation 145 to manage interrupts while the system of external devices is in operation. The condition management system 150 may operate in accordance with the U.S. Patent Application

Serial No. 10/612,097 entitled "A Condition Management System and Method of Operation Thereof," previously incorporated by reference. The hierarchical register consolidation structure contains a logical representation of the microprocessor-accessible registers, node interrelationships, summary bits and masks of the system of external devices and therefore relieves the CMS 150 of the task of conforming itself to the physical configuration of the registers, interrelationships, bits and masks.

[0025] In the illustrated embodiment of the present invention, the graph generator 110, the graph converter 120 and the description generator 130 are embodied in sequences of instructions executable in a general purpose computing system. Of course, the graph generator 110, the graph converter 120 and the description generator 130 could be implemented in hardware, firmware or any suitable combination of hardware, firmware or software.

[0026] Turning now to FIGURE 2, illustrated is a flow diagram of a method, generally designated 200, of automatically generating a hierarchical register consolidation structure carried out according to the principles of the present invention. The method 200 begins in a start step 210, wherein a HDL file is in existence, and it is desired to generate a hierarchical register consolidation structure from the HDL file.

[0027] The method 200 proceeds to a step 220 in which a HDL file is parsed to generate an intermediate graph containing definitions

of microprocessor-accessible registers, node interrelationships and summary bits, bit offsets and masks associated with alarm registers. In the embodiment illustrated in FIGURE 1, the parsing is done in three passes. First, definitions of all the microprocessor accessible registers, register names, addresses, bit positions used and their names are extracted. Second, node interrelationships are identified and alarm registers are associated with their mask register and persistency and delta information. Third, summary bits in an alarm register are associated with the alarm register that is summarized, and bit offsets and masks are generated.

[0028] Next, in a step 230, virtual elements and nodes are selectively added to the intermediate graph to transform the intermediate graph into a mathematical tree. Modification and/or pruning of the graph may be required to make it a true mathematical tree or desired to make it smaller or more efficient.

[0029] Then, in a step 240, the mathematical tree is employed to generate a static tree description in a programming language suitable for use by a device-independent condition management structure (C, in the illustrated embodiment). As has been demonstrated above, the static tree description can contain both node and element descriptions. Next, in a step 250, the static tree description is employed to generate an HTML traversable tree

representation based on the mathematical tree. The method 200 then ends in an end step 260.

[0030] Although the present invention has been described in detail, those skilled in the art should understand that they can make various changes, substitutions and alterations herein without departing from the spirit and scope of the invention in its broadest form.